



DIMENSION TABLE (MODEL WITHOUT BRAKE)

MODEL	LL	LR	LS	S	LW	WK	W	T	RH	TP
ECMA-E□1820AS	169				---	---	---	---	---	M12, Depth 25
ECMA-E□1820CS					63	10	10	8	30	
ECMA-E□1820PS					---	---	---	---	---	
ECMA-E□1820RS					---	---	---	---	---	
ECMA-F□1830AS	202.1	79	73	35	---	---	---	---	---	
ECMA-F□1830CS					63	10	10	8	30	
ECMA-F□1830PS					---	---	---	---	---	
ECMA-F□1830RS					---	---	---	---	---	
ECMA-E□1835AS	235.3				---	---	---	---	---	
ECMA-E□1835CS					63	10	10	8	30	
ECMA-E□1835PS					---	---	---	---	---	
ECMA-E□1835RS					---	---	---	---	---	
ECMA-F□1845AS	235.3				---	---	---	---	---	
ECMA-F□1845CS					63	10	10	8	30	
ECMA-F□1845PS					---	---	---	---	---	
ECMA-F□1845RS	---	---	---	---	---	---	---	---	---	



SHAFT END DETAILS



KEY DETAILS

台達電子工業股份有限公司 DELTA ELECTRONICS, INC.	DRAWN:	DESIGN:
	DATE:	ECN NO.:
THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF DELTA ELECTRONICS, INC. AND SHALL NOT BE REPRODUCED OR USED AS THE BASIS FOR THE MANUFACTURE OR SELL OF APPARATUS OR DEVICES WITHOUT PERMISSION.	DIMENSIONAL TOLERANCES ( ) ( ) ( ) ANGLES DECIMALS 0~4 ±0.05 <50 ±0.1 <50 ±0.5 <30° ±0.1° X ±0.3 4~16 ±0.08 >50~100 ±0.15 >100~200 ±0.2 >200~400 ±0.3 X.X ±0.2 16~63 ±0.12 >100~200 ±0.2 >100~200 ±1.5 >60°~90° ±0.5° X.XX ±0.1 63~200 ±0.2 >200~ ±0.2% >200~ ±0.3%	
	DRAWING NAME: MOTOR_F180_1.5~4.5KW	A3 SIZE THIRD ANGLE PROJECTION
USED ON	UNIT mm	SHEET 1 OF 1